

Northumbria Research Link

Citation: Debashi, Mohamed and Vickers, Paul (2018) Sonification of Network Traffic Flow for Monitoring and Situational Awareness. PLoS ONE, 13 (4). e0195948. ISSN 1932-6203

Published by: Public Library of Science

URL: <http://doi.org/10.1371/journal.pone.0195948> <<http://doi.org/10.1371/journal.pone.0195948>>

This version was downloaded from Northumbria Research Link: <http://nrl.northumbria.ac.uk/33954/>

Northumbria University has developed Northumbria Research Link (NRL) to enable users to access the University's research output. Copyright © and moral rights for items on NRL are retained by the individual author(s) and/or other copyright owners. Single copies of full items can be reproduced, displayed or performed, and given to third parties in any format or medium for personal research or study, educational, or not-for-profit purposes without prior permission or charge, provided the authors, title and full bibliographic details are given, as well as a hyperlink and/or URL to the original metadata page. The content must not be changed in any way. Full items must not be sold commercially in any format or medium without formal permission of the copyright holder. The full policy is available online: <http://nrl.northumbria.ac.uk/policies.html>

This document may differ from the final, published version of the research and has been made available online in accordance with publisher policies. To read and/or cite from the published version of the research, please visit the publisher's website (a subscription may be required.)



**Northumbria
University**
NEWCASTLE



UniversityLibrary

S1 Appendix — SoNSTAR: flow and IP flow feature information array contents

When a TCP packet is received, the Feature Extractor unpacks the packet and extracts the flag status. The system has a counter which counts the packets arriving in each time window. For every packet which arrives in the time window, the Features Extractor extracts the flag status. If this flow has not been seen before it creates a new Traffic flow or IP flow if it does not already exist; if the flow already exists then it updates the flag counts for the two types of TCP protocol flows as follows.

1 Traffic Flows

Traffic Flows identified by `src_addr`, `src_port`, `dst_addr` and `dst_port` are followed by columns with flag status counts. SoNSTAR retains the information in an array carrying all feature information extracted from the packets in each time window for each Traffic flow as per Table 1.

Table 1: Feature information array: Traffic flow

Element	Label	Description
1	Flow Counter	This represents the number of flows in each time window.
2	Address 1	This is one of the IP addresses of the flow which changes to be the source or destination according to the side sending or receiving the packet.
3	Address 2	This is one of the IP addresses of the flow which changes to be the source or destination according to the side sending or receiving the packet.
4	Port 1	This is one of the ports of the flow which changes to be the source or destination according to the side sending or receiving the packet.
5	Port 2	This is one of the ports of the flow which changes to be the source or destination according to the side sending or receiving the packet.
6	FIN Out	Counts of outgoing FINs packets, which represent the total counts of outgoing packets which hold FIN status set to 1 and the status of other flags is set to 0.
7	FIN In	Counts of incoming FINs packets., which represent the total counts of incoming packets which hold FIN status set to 1 and the status of other flags is set to 0.
8	SYN Out	Counts of outgoing SYN packets, which represent the total counts of outgoing packets which hold SYN status set to 1 and the status of other flags is set to 0.
9	SYN In	Counts of incoming SYN packets, which represent the total counts of incoming packets which hold SYN status set to 1 and the status of other flags is set to 0.
10	SYN ACK Out	Counts of outgoing SYN-ACKs packets, which represent the total counts of outgoing packets which hold SYN and ACK status set to 1 and the status of other flags is set to 0.
11	SYN ACK In	Counts of incoming SYN-ACKs packets, which represent the total counts of incoming packets which hold SYN and ACK status set to 1 and the status of other flags is set to 0.
12	RST Out	Counts of outgoing RSTs packets, which represent the total counts of outgoing packets which hold RST status set to 1 and the status of other flags is set to 0.
13	RST In	Counts of incoming RSTs packets, which represent the total counts of incoming packets which hold RST status set to 1 and the status of other flags is set to 0.
14	ACK Out	Counts of outgoing ACKs packets, which represent the total counts of outgoing packets which hold ACK status set to 1 and the status of other flags is set to 0.
15	ACK In	Counts of incoming ACKs packets, which represent the total counts of incoming packets which hold ACK status set to 1 and the status of other flags is set to 0.
16	PSH Out	Counts of outgoing PSH packets, which represent the total counts of outgoing packets which hold PSH status set to 1 and the status of other flags is set to 0.
17	PSH In	Counts of incoming PSH packets, which represent the total counts of incoming packets which hold PSH status set to 1 and the status of other flags is set to 0.
18	PSH ACK Out	Counts of outgoing PSH-ACK packets, which represent the total counts of outgoing packets which hold PSH status set to 1 and ACK status set to 1 and the status of other flags is set to 0.

Continued on next page

Table 1 – Continued from previous page

Element	Label	Description
19	PSH ACK In	Counts of incoming PSH-ACK packets, which represent the total counts of incoming packets which hold PSH status set to 1 and ACK status set to 1 and the status of other flags is set to 0.
20	URG Out	Counts of outgoing URG packets, which represent the total counts of outgoing packets which hold URG status set to 1 and the status of other flags is set to 0.
21	URG In	Counts of incoming URG packets, which represent the total counts of incoming packets which hold URG status set to 1 and the status of other flags is set to 0.

2 IP flows

IP flow identified by `src_addr` and `dst_addr` are followed by columns of flag status counts. SoNSTAR retains the information in an array carrying all feature information extracted from the packets in each time window for each IP flow as per Table 2.

Table 2: Feature information array: IP-flow

Element	Label	Description
1	IP Flow Counter	This represents the number of IP flows in each time window.
2	Address 1	This is one of the IP addresses of the flow which changes to be the source or destination according to the side sending or receiving the packet.
3	Address 2	This is one of the IP addresses of the flow which changes to be the source or destination according to the side sending or receiving the packet.
4	FIN Out IPs	Counts of outgoing FINs packets between two IP addresses for whole ports, which represent the total counts of outgoing packets which hold FIN status set to 1 and the status of other flags is set to 0.
5	FIN In IPs	Counts of incoming FINs packets between two IP addresses for whole ports, which represent the total counts of incoming packets holds FIN status set to 1 and the status of other flags is set to 0.
6	SYN Out IPs	Counts of outgoing SYN packets between two IP addresses for whole ports, which represent the total counts of outgoing packets which hold SYN status set to 1 and the status of other flags is set to 0.
7	SYN In IPs	Counts of incoming SYN packets between two IP addresses for whole ports, which represent the total counts of incoming packets which hold SYN status set to 1 and the status of other flags is set to 0.
8	SYN ACK Out IPs	Counts of outgoing SYN-ACKs packets between two IP addresses for whole ports, which represent the total counts of outgoing packets which hold SYN and ACK status set to 1 and the status of other flags is set to 0.
9	SYN ACK In IPs	Counts of incoming SYN-ACKs packets between two IP addresses for whole ports, which represent the total counts of incoming packets which hold SYN and ACK status set to 1 and the status of other flags is set to 0.
10	RST Out IPs	Counts of outgoing RSTs packets between two IP addresses for whole ports, which represent the total counts of outgoing packets which hold RST status set to 1 and the status of other flags is set to 0.
11	RST In IPs	Counts of incoming RSTs packets between two IP addresses for whole ports, which represent the total counts of incoming packets which hold RST status set to 1 and the status of other flags is set to 0.
12	ACK Out IPs	Counts of outgoing ACKs packets between two IP addresses for whole ports, which represent the total counts of outgoing packets which hold ACK status set to 1 and the status of other flags is set to 0.
13	ACK In IPs	Counts of incoming ACKs packets between two IP addresses for whole ports, which represent the total counts of incoming packets which hold ACK status set to 1 and the status of other flags is set to 0.
14	PSH Out IPs	Counts of outgoing PSH packets between two IP addresses for whole ports, which represent the total counts of outgoing packets which hold PSH status set to 1 and the status of other flags is set to 0.
15	PSH In IPs	Counts of incoming PSH packets between two IP addresses for whole ports, which represent the total counts of incoming packets which hold PSH status set to 1 and the status of other flags is set to 0.
16	PSH ACK Out IPs	Counts of outgoing PSH-ACK packets between two IP addresses for whole ports, which represent the total counts of outgoing packets which hold PSH status set to 1 and ACK status set to 1 and the status of other flags is set to 0.

Continued on next page

Table 2 – Continued from previous page

Element	Label	Description
17	PSH ACK In IPs	Counts of incoming PSH-ACK packets between two IP addresses for whole ports, which represent the total counts of incoming packets which hold PSH status set to 1 and ACK status set to 1 and the status of other flags is set to 0.
18	URG Out IPs	Counts of outgoing URG packets between two IP addresses for whole ports, which represent the total counts of outgoing packets which hold URG status set to 1 and the status of other flags is set to 0.
19	URG In IPs	Counts of incoming URG packets between two IP addresses for whole ports, which represent the total counts of incoming packets which hold URG status set to 1 and the status of other flags is set to 0.
20	URG PSH FIN Out IPs	Counts of outgoing URG-PSH-FIN packets between two IP addresses for all ports, which represent the total counts of outgoing packets which hold URG and PSH and FIN status set to 1 and the status of other flags is set to 0.
21	URG PSH FIN In IPs	Counts of incoming URG-PSH-FIN packets between two IP addresses for wholeall ports, which represent the total counts of incoming packets which hold URG and PSH and FIN status set to 1 and the status of other flags is set to 0.
22	NULL Out IPs	Counts of outgoing NULL packets between two IP addresses for all ports, which represent the total counts of outgoing packets which hold all flags with status set to 0.
23	NULL In IPs	Counts of incoming NULL packets between two IP addresses for all ports, which represent the total counts of incoming packets which hold all flags with status set to 0.
24	LAND Out IPs	Counts of outgoing LAND packets between two IP addresses for all ports, which represent the total counts of outgoing packets which have the same source and destination IP addresses.
25	LAND In IPs	Counts of incoming LAND packets between two IP addresses for all ports, which represent the total counts of incoming packets which have the same source and destination IP addresses.